

Up to Category 4, EN 954-1 PNOZ XV1P




Safety relay for monitoring E-STOP pushbuttons and safety gates.

Approvals

	PNOZ XV1P
	◆
	◆
	◆

Block diagram



Unit features

- ▶ Positive-guided relay outputs:
 - 2 safety contacts (N/O), instantaneous
 - 1 safety contact (N/O), delay-on de-energisation
- ▶ Connection options for:
 - E-STOP pushbutton
 - Safety gate limit switch
 - Reset button
- ▶ LED indicator for:
 - Switch status channel 1/2
 - Supply voltage
- ▶ Plug-in connection terminals (either cage clamp terminal or screw terminal)
- ▶ See order reference for unit types

Safety features

- The relay conforms to the following safety criteria:
- ▶ The circuit is redundant with built-in self-monitoring.
 - ▶ The safety function remains effective in the case of a component failure.
 - ▶ The correct opening and closing of the safety function relays is tested automatically in each on-off cycle.
 - ▶ The unit has an electronic fuse.

Unit description

The safety relay meets the requirements of EN 60204-1 and IEC 60204-1 and may be used in applications with

- ▶ E-STOP pushbuttons
 - ▶ Safety gates
- The max. category the safety contacts can achieve in accordance with EN 954-1 is stated in the technical details.

Up to Category 4, EN 954-1 PNOZ XV1P


Function description

- ▶ Single-channel operation: no redundancy in the input circuit, earth faults in the reset and input circuit are detected.
- ▶ Dual-channel operation with detection of shorts across contacts: redundant input circuit, detects
 - earth faults in the reset and input circuit,
 - short circuits in the input circuit

- and, with a monitored reset, in the reset circuit too,
 - shorts between contacts in the input circuit.
- ▶ Dual-channel operation without detection of shorts across contacts: redundant input circuit, detects
 - earth faults in the reset and input circuit,
 - short circuits in the input circuit and, with a monitored reset, in the reset circuit too.

- ▶ Automatic start: Unit is active once the input circuit has been closed.
- ▶ Monitored reset: Unit is active once the input circuit is closed and once the reset circuit is closed after the waiting period has elapsed (see technical details).
- ▶ Increase in the number of available contacts by connecting contact expander modules or external contactors/relays.

Timing diagram



Key

- ▶ Power: Supply voltage
- ▶ Reset/start: Reset circuit S14-S32, S33-S34
- ▶ Reset t_v: Y39-Y40
- ▶ Input: Input circuits S11-S12, S12-S32, S21-S22
- ▶ Output safe: Safety contacts, instantaneous 13-14, 23-24
- ▶ Output safe del: Safety contacts, delayed 37-38
- ▶ ①: Automatic reset
- ▶ ②: Monitored reset
- ▶ t₁: Switch-on delay
- ▶ t₂: Delay-on de-energisation
- ▶ t₃: Delay time
- ▶ t₄: Waiting period

Wiring

Please note:

- ▶ Information given in the “Technical details” must be followed.
- ▶ Outputs 37-38 are delay-on de-energisation safety contacts.
- ▶ To prevent contact welding, a fuse should be connected before the output contacts (see technical details).
- ▶ Calculation of the max. cable runs I_{max} in the input circuit:

$$I_{\max} = \frac{R_{l\max}}{R_l / \text{km}}$$

R_{lmax} = max. overall cable resistance (see technical details)

R_l/km = cable resistance/km

Up to Category 4, EN 954-1 PNOZ XV1P

Preparing for operation

- ▶ Supply voltage

Supply voltage	AC	DC

- ▶ Input circuit

Input circuit	Single-channel	Dual-channel
E-STOP without detection of shorts across contacts		
E-STOP with detection of shorts across contacts		
Safety gate without detection of shorts across contacts		
Safety gate with detection of shorts across contacts		

Up to Category 4, EN 954-1 PNOZ XV1P

► Reset circuit

Reset circuit	E-STOP wiring, safety gate	Safety gate (dual-channel)
Automatic reset		
Monitored reset		

► Feedback loop


Feedback loop	Automatic reset	Monitored reset
Contacts from external contactors		

► Key

S1/S2	E-STOP pushbutton/ safety gate switch
S3	Reset button
↑	Switch operated
↗	Gate open
↘	Gate closed

Up to Category 4, EN 954-1 PNOZ XV1P

Terminal configuration




Installation

- ▶ The safety relay should be installed in a control cabinet with a protection type of at least IP54.
- ▶ Use the notch on the rear of the unit to attach it to a DIN rail.
- ▶ Ensure the unit is mounted securely on a vertical DIN rail (35 mm) by using a fixing element (e.g. retaining bracket or an end angle).

Dimensions

* with cage clamp terminals




Up to Category 4, EN 954-1 PNOZ XV1P

Notice

This data sheet is only intended for use during configuration. For installation and operation, please refer to the operating instructions supplied with the unit.

Service life graph



Technical details

Electrical data

Supply voltage U_B DC	24 V
Voltage tolerance	-15% / +10%
Power consumption	3.5 W
Residual ripple DC	20 %
Voltage and current at input circuit: 24.0 VDC	35.0 mA
reset circuit: 24.0 VDC	35.0 mA
feedback loop: 24.0 VDC	1.0 mA
Output contacts in accordance with EN 954-1 , Category 4	Safety contacts (N/O): 2 ST
Output contacts in accordance with EN 954-1	Safety contacts (N/O), delayed: 1 ST
Category 1 Order no. 777602, 787602	When delay time >30 s
Category 3	When delay time <30 s
Utilisation category in accordance with EN 60947-4-1	
AC1: 240 V	$I_{min}: 0.01 \text{ A}, I_{max}: 5.0 \text{ A}$ $P_{max}: 1,250 \text{ VA}$
DC1: 24 V	$I_{min}: 0.01 \text{ A}, I_{max}: 5.0 \text{ A}$ $P_{max}: 125 \text{ W}$
Utilisation category in accordance with EN 60947-5-1 :	
Inst. contacts	
AC15: 230 V	$I_{max}: 1.5 \text{ A}$
DC13 (6 cycles/min): 24 V	$I_{max}: 2.0 \text{ A}$
Utilisation category in accordance with EN 60947-5-1 :	
Delayed contacts	
AC15: 230 V	$I_{max}: 2.0 \text{ A}$
DC13 (6 cycles/min): 24 V	$I_{max}: 4.0 \text{ A}$
Contact material	AgSnO₂ + 0.2 μm Au
External contact fuse protection (EN 60947-5-1)	
Blow-out fuse, quick	6 A
Blow-out fuse, slow	4 A
Circuit breaker	4 A , 24 VAC/DC, characteristic B/C
Max. overall cable resistance R_{lmax} input circuits, reset circuits	
Single-channel	100 Ohm
Dual-channel without detection of shorts across contacts	150 Ohm
Dual-channel with detection of shorts across contacts	15 Ohm

Up to Category 4, EN 954-1 PNOZ XV1P

Times

Switch-on delay with automatic reset typ.	350 ms
with automatic reset max.	650 ms
with automatic reset after power on typ.	350 ms
with automatic reset after power on max.	650 ms
with monitored reset typ.	30 ms
with monitored reset max.	60 ms

Delay-on de-energisation with E-STOP typ.	15 ms
with E-STOP max.	30 ms
with power failure typ.	80 ms
with power failure max.	250 ms

Recovery time at max. switching frequency 1/s after E-STOP	50 ms + t_v
after power failure	300 ms

Delay time t_v selectable	0.10 s – 3.00 s Order no.: 777601, 787601 1.00 s – 30.00 s Order no.: 777602, 787602
-----------------------------	---

Repetition accuracy	2 %
Time accuracy	-20% / +20%

Waiting period with a monitored reset	300 ms
Min. start pulse duration with a monitored reset	30 ms

Simultaneity, channel 1 and 2	∞
Supply interruption before de-energisation	20 ms

Environmental data

EMC	EN 60947-5-1, EN 61000-6-2, EN 61000-6-3
Vibration in accordance with EN 60068-2-6	
Frequency	10 - 55 Hz
Amplitude	0.35 mm
Climatic suitability	EN 60068-2-78
Airgap creepage	VDE 0110-1
Ambient temperature	-10 - 55 °C
Storage temperature	-40 - 85 °C
Protection type	IP54
Mounting (e.g. cabinet)	IP40
Housing	IP20
Terminals	

Mechanical data

Housing material	PPO UL 94 V0
Housing	ABS UL 94 V0
Front	
Max. cross section of external conductors with screw terminals	
1 core flexible	0.25 – 2.50 mm ²
2 core, same cross section, flexible:	
with crimp connectors, without insulating sleeve	0.25 – 1.00 mm ²
without crimp connectors or with TWIN crimp connectors	0.20 – 1.50 mm ²
Torque setting with screw terminals	0.50 Nm
Max. cross section of external conductors with cage clamp terminals: flexible without crimp connectors	0.20 – 1.50 mm ²
Cage clamp terminals	
Terminal points per connection	2
Stripping length	8 mm
Dimensions (H x W x D)	
with screw terminals	94.0 mm x 22.5 mm x 121.0 mm
with cage clamp terminals	101.0 mm x 22.5 mm x 121.0 mm
Weight	220 g

The standards current on 09/03 apply.

Up to Category 4, EN 954-1 PNOZ XV1P

Max. continuous current

Number of contacts	I_{max} (A) at U_B DC
1	5.00 A
2	3.70 A
3	3.00 A

Order reference

Type	Features	Terminals	Order no.
PNOZ XV1P	24 VDC	3 s selectable	Screw terminals 777 601
PNOZ XV1P C	24 VDC	3 s selectable	Cage clamp terminals 787 601
PNOZ XV1P	24 VDC	30 s selectable	Screw terminals 777 602
PNOZ XV1P C	24 VDC	30 s selectable	Cage clamp terminals 787 602